



**Standard Specification Sheet Model: MS4421**  
**Low Cost, Space Saving AC Voltage Transducer**

MS4400

**OVERVIEW**



This is low cost, space saving AC Voltage transducer that converts AC voltage signal from PT into any desired standard process signal.

- ▽ Durable for waveform, thus enabling application for inverter measurement.
- ▽ Wide allowance for power source voltage: 85~264V AC / 85~143V DC
- ▽ Low cost, space saving, light weight, low power consumption – Helps saving total cost and environmental burden at the same time.

**ORDERING INFORMATION**

Ordering Code	Standard Price
MS4421	OPEN

**PECIFICATIONS**

**Input Specifications**

Input Signal (Specify at ① when ordering)	<ul style="list-style-type: none"> <li>■ 0~150V AC..... 1</li> <li>■ 0~300V AC..... 2</li> <li>■ 0~63.5V AC..... 3</li> <li>■ Others ..... 4</li> </ul>
Rated Frequency	50/60Hz combined
Power Consumption	Measurement Input: 0.3VA max. Auxiliary Power Input: 2VA max.
Continuous Overload	120% of rated input value
Instantaneous Overload	Twice rated voltage (10s)

**Output Specifications**

Output Signal (Specify at ② when ordering)	<ul style="list-style-type: none"> <li>■ 4~20mA DC (Load Resistance 600 Ω max.)..... A</li> <li>■ 0~1mA DC (Load Resistance 10k Ω max.)..... B</li> <li>■ 1~5V DC (Load Resistance 1k Ω min.) C</li> <li>■ 0~5V DC (Load Resistance 1k Ω min.) D</li> <li>■ 0~10V DC (Load Resistance 1k Ω min.) E</li> <li>■ Specified range ..... Z</li> </ul>
--	--

**Power Specifications**

Auxiliary Power Supply (Specify at ③ when ordering)	<ul style="list-style-type: none"> <li>■ AC85~264V/DC88~143V ..... 1</li> <li>■ DC20~30V (+¥10,000) ..... 2</li> <li>■ DC40~60V (+¥10,000) ..... 3</li> </ul>
---	---

**Device Specifications**

Construction	Boxed Construction with front terminal
Connection Method	M4 Screw Terminal
Case Material	Flame retardant black resin
Zero Adjustment	Approx. 5%
Span Adjustment	Approx. 5%

**Physical Specifications**

Operating Temperature Range	-10~55°C
Operating Humidity Range	40~85%RH
Storage Temperature Range	-40~70°C
Shock	Apply the shock of magnitude 490m/s <sup>2</sup> specified in Test Method 1 of JIS C 0912 3 times each in forward and reverse directions along three axes at right angles each other selected to include the mounting face, 18 times in total
Vibration	Apply the vibration with vibration frequency of 16.7Hz and vibration displacement of 4mm in peak-to-peak amplitude specified in 4.2 of JIS C 0911, in the directions of 3 axes at right angles each other including the mounting face each for 1h, for 3h in total
Mounting	Wall-mount or DIN-rail-mount
Weight	Approx. 200g

## Performance

Compliance Standard	JIS C 1111
Tolerance	$\pm 0.5\%$ (Relative to output span)
Output Ripple	1%p-p max. (Relative to output span)
Response Time	0.5s max. (time until the output reaches and remains with a band $\pm 1\%$ of the rated output when input steps from 0 to 90%)
Effect of Self-heating	$\pm 0.5\%$ (Relative to output span)
Effect of Temperature	$\pm 0.5\%$ (Relative to output span) Value obtained with $23 \pm 20^\circ\text{C}$ variation of ambient temperature
Effect of Frequency	$\pm 0.25\%$ (Relative to output span) Value obtained with $\pm 5\%$ variation of rated frequency
Effect of External Magnetic Field	$\pm 0.5\%$ (Relative to output span) Value obtained with magnetic field of 400A/m
Effect of Auxiliary Power Supply Voltage	$\pm 0.25\%$ (Relative to output span) Over full supply voltage range
Effect of Output Load	$\pm 0.25\%$ (Relative to output span) Value obtained with variation of full range within rated output load
Effect of Waveform	$\pm 0.5\%$ (Relative to output span) Value obtained with input including third higher harmonic equal to $\pm 20\%$ of the fundamental wave
Insulation Resistance	Measure with DC500V insulation resistance tester <ul style="list-style-type: none"> <li>Between all electrical circuits connected together and ground terminal: <math>50\text{M}\Omega</math> min.</li> <li>Between input terminals connected together and output terminals connected together: <math>50\text{M}\Omega</math> min.</li> <li>Between auxiliary power supply terminals connected together and input and output terminals connected together: <math>50\text{M}\Omega</math> min.</li> </ul>
Power Frequency Withstand Voltage	Test by applying AC2000V for 1 min. <ul style="list-style-type: none"> <li>Between all electrical circuits connected together and ground terminal</li> <li>Between input terminals connected together and output terminals connected together</li> <li>Between auxiliary power supply terminals connected together and input and output terminals connected together</li> </ul>
Lightning Impulse Withstand Voltage	Apply voltage waveform of $1.2/50 \mu\text{s}$ with full wave voltage 6kV <ul style="list-style-type: none"> <li>Between all electrical circuits connected together and ground terminal</li> <li>Between input terminals connected together and output terminals connected together</li> </ul> <p>Apply current waveform of <math>\pm 8/20 \mu\text{s}</math> with full wave voltage 2000V</p> <ul style="list-style-type: none"> <li>Between output terminals</li> </ul>

## CONNECTION DIAGRAM

## Terminal Numbers

